

LG BASIC 3715

Operating Features
Of the Electronic Combination Lock

SAFE & VAULT MANUFACTURERS

1. ANTI TAMPER FEATURE:

Entering Four (4) wrong sets of numbers in a row, puts the lock into an 8-minute lock out penalty time in which the lock is inoperable.

At the end of the 8-minute duration, the lock is ready for the correct number, a further one (1) incorrect entry will put the lock into penalty time again, only the correct number will open and reset the lock.

2. LOW BATTERY INDICATION:

Multiple beeps at the end of a code number entry means the battery needs replacing.

3. CHANGING YOUR BATTERY:

·Slide the keypad housing up and carefully pull away from mounting surface to expose battery compartment.

·Remove 9- volt Alkaline battery and replace with a new one.

·The connector is easily removed by unsnapping it from the two terminals on the top of the battery.



CAUTION! HOLD ONTO BATTERY TERMINAL TO AVOID PULLING WIRES OUT OF HOUSING

·Carefully position the keypad over the mounting screws and slide the keypad housing down. Ensure that there are no wires or cables trapped between the input pad and the safe door. Pinched cables can result in a short circuit.

4. BATTERY TYPE:

Use Duracell Procell Alkaline 9 volt batteries only.



NOTE

The lock does not lose any memory if the batteries are disconnected for any length of time. Battery life is dependent on the amount of use, an opening per day approx. 12 months life. Higher use, reduced battery life. Poor quality batteries can reduce operational life by up to 50%.



TO OPEN:

Enter 1 2 3 4 5 6 (Factory setting)

Each number is accompanied by a BEEP.

2 Beeps after 6 digit code entered signifies number accepted.

3 Beeps after 6 digit code entered indicates wrong number.



TO LOCK:

Close Safe door and Turn handle to close position.

The lock will lock automatically.



TO CHANGE NUMBER:

CAUTION: Change code with door open & locked

1. Enter 0 0 0 0 0 0 (6 zero's)

2. Enter the old code (Factory set 1 2 3 4 5 6)

3. Enter new code twice e.g. (142536 + 142536)

4. 2 beeps signify new code has been accepted.

5. Test new number.



NOTE

The code remains existing if the above steps are not followed correctly.



Use ALKALINE Batteries Only

For any further information on this lock or any CMI Safe Co products contact your nearest Distributor or CMI Safe Co.



Call us for more info

(02) 9547 1488

CMI SAFE CO AUSTRALASIA PTY LTD
SINCE 1946 AUSTRALIA'S LEADING SAFE & VAULT MANUFACTURER



244 West Street, Carlton, NSW 2218



www.cmisafe.com.au



sales@cmisafe.com.au

Agents in all major Cities throughout Australia

